

Datasheet LAR 22 S

12Vcc / 24Vac dual power cabinet power supply

Power supply designed to offer an additional power supply station independent of the alarm control unit, as the columns need 12V power supply for the circuit section and 24V power supply for the heaters. Enough power can be inserted in the well to provide power for up to 5 columns (8 total beams per column: 4RX + 4TX).

CHARACTERISTIC	
Topology	Linear power supply with 300VA toroid
Input	220Vac 50/60HZ (with delayed fuse protection)
Outputs	2 With voltage of 13.8 Vdc 2.5A (with delayed fuse protection)
	2 With voltage of 24 Vac 10A (with delayed fuse protection)
	1 Backup Battery 12V 17AH Max
Power	300W
Ausiliary outputs	Presence of output voltage, low output voltage, line voltage absent NC to GND
Led	3 status indicators
Tamper	Anti-opening protection
Dimensions	300 x 380 x 90 mm
Weight	6,5 Kg

